

# ESPHOME

## ESP32 cam

```
#!/bin/sh

TOKEN=...

PAYLOAD="{\"directive\": {\"header\": {\"namespace\": \"Alexa.Discovery\",
\"name\": \"Discover\", \"payloadVersion\": \"3\", \"messageId\":
\"8db404f7-f5a1-495e-9a30-3a8af3bf94e0\"}, \"payload\": {\"scope\":
{\"type\": \"BearerToken\", \"token\": \"...\"}}}}}"

curl -q -X POST \
-d "$PAYLOAD" \
-H "Authorization: Bearer $TOKEN" \
-H "Content-Type: application/json" \
http://localhost:8123/api/alexasmart_home | jq
'.event.payload.endpoints[] | select(.displayCategories[0]=="CAMERA")'
```

esp32 entry (missing some values)

```
{
  "displayCategories": [
    "CAMERA"
  ],
  "cookie": {},
  "endpointId": "camera#citofono",
  "friendlyName": "citofono",
  "description": "camera.citofono via Home Assistant",
  "manufacturerName": "Home Assistant",
  "additionalAttributes": {
    "manufacturer": "Home Assistant",
    "model": "camera",
    "softwareVersion": "2021.6.6",
    "customIdentifier": "-camera.citofono"
  },
  "capabilities": [
    {
      "type": "AlexaInterface",
      "interface": "Alexa.EndpointHealth",
      "version": "3",
      "properties": {
        "supported": [
          {
            "name": "connectivity"
          }
        ]
      }
    }
  ]
}
```

```
    ],  
    "proactivelyReported": true,  
    "retrievable": true  
  }  
},  
{  
  "type": "AlexaInterface",  
  "interface": "Alexa",  
  "version": "3"  
}  
]  
}
```

valid stream camera working in alexa

```
{  
  "displayCategories": [  
    "CAMERA"  
  ],  
  "cookie": {},  
  "endpointId": "camera#cancello",  
  "friendlyName": "camera cancello",  
  "description": "camera.cancello via Home Assistant",  
  "manufacturerName": "Home Assistant",  
  "additionalAttributes": {  
    "manufacturer": "Home Assistant",  
    "model": "camera",  
    "softwareVersion": "2021.6.6",  
    "customIdentifier": "-camera.cancello"  
  },  
  "capabilities": [  
    {  
      "type": "AlexaInterface",  
      "interface": "Alexa.CameraStreamController",  
      "version": "3",  
      "cameraStreamConfigurations": [  
        {  
          "protocols": [  
            "HLS"  
          ],  
          "resolutions": [  
            {  
              "width": 1280,  
              "height": 720  
            }  
          ],  
          "authorizationTypes": [  
            "NONE"  
          ],  
          "videoCodecs": [  

```

```
        "H264"  
      ],  
      "audioCodecs": [  
        "AAC"  
      ]  
    }  
  ],  
  {  
    "type": "AlexaInterface",  
    "interface": "Alexa.EndpointHealth",  
    "version": "3",  
    "properties": {  
      "supported": [  
        {  
          "name": "connectivity"  
        }  
      ],  
      "proactivelyReported": true,  
      "retrievable": true  
    }  
  },  
  {  
    "type": "AlexaInterface",  
    "interface": "Alexa",  
    "version": "3"  
  }  
]  
}
```

## BLE tracker smartband

### esphome

enable esp32\_ble\_tracker and a binary sensor on ble\_presence

```
esp32_ble_tracker:  
  
binary_sensor:  
  - platform: ble_presence  
    mac_address: E8:36:FD:20:E3:54  
    id: miband_presence_scipio  
    name: "MiBand presence scipio"
```

### hass

automation directly on sensor created by esphome

```
- alias: cancello
  trigger:
    - entity_id: binary_sensor.miband_presence_scipio
      platform: state
      to: 'on'
      for:
        seconds: 2
    - entity_id: binary_sensor.miband_presence_scipio
      platform: state
      to: 'off'
      for:
        seconds: 2
  action:
    - service: notify.alexa_media
      data_template:
        message: >
          {% if is_state('binary_sensor.miband_presence_scipio', 'on') %}
            'Stefano è arrivato'
          {% else %}
            'Stefano è partito'
          {% endif %}
        data:
          type: announce
          method: all
        target:
          - show
          - Echo
```

example of added binary sensor defined on ble sensor

```
binary_sensor:
  - platform: template
    sensors:
      miband_scipio_sticky:
        value_template: >-
          {{is_state('binary_sensor.miband_presence_scipio', 'on')}}
        delay_off: 60
```

## BLE bluetooth tracker (version 1)

hass input\_boolean:

```
beacon2_learn:
  name: learn beacon2
  initial: off
  icon: mdi:mdi-tag-plus

beacon2_active:
```

```
name: beacon2 is recently seen
icon: mdi:mdi-account-check
```

*beacon2\_trigger:*

```
name: beacon2 is now detected
initial: off
icon: mdi:mdi-account-check
```

hass input\_text:

```
beacon1:
  name: BLE beacon1

beacon2:
  name: BLE beacon2
```

hass scripts:

```
set_ibeacon:
  sequence:
    - condition: template
      value_template: "{{ ibeacon != '' }}"
    - service: script.set_beacon1
      data_template:
        ibeacon: "{{ ibeacon }}"
    - service: script.set_beacon2
      data_template:
        ibeacon: "{{ ibeacon }}"

set_beacon2:
  sequence:
    - service: script.beacon2_active
      data_template:
        ibeacon: "{{ ibeacon }}"
    - condition: state
      entity_id: input_boolean.beacon2_learn
      state: "on"
    - service: input_text.set_value
      data_template:
        entity_id: input_text.beacon2
        value: "{{ ibeacon }}"
    - service: input_boolean.turn_off
      entity_id: input_boolean.beacon2_learn

beacon2_active:
  sequence:
    - condition: template
      value_template: "{{ ibeacon == states('input_text.beacon2') }}"
    - service: input_boolean.turn_on
      entity_id: input_boolean.beacon2_trigger
    - delay: 1
```

```
- service: input_boolean.turn_off  
  entity_id: input_boolean.beacon2_trigger
```

hass automations:

```
- alias: "beacon2 is active"  
  trigger:  
    platform: state  
    entity_id: input_sensor.beacon2_trigger  
    to: "on"  
  condition:  
    condition: state  
    entity_id: input_boolean.beacon2_active  
    state: "off"  
  action:  
    - service: input_boolean.turn_on  
      entity_id: input_boolean.beacon2_active  
    - service: notify.alexa_media  
      data:  
        message: "Stefano è arrivato"  
        data:  
          type: announce  
          method: all  
        target:  
          - show  
          - Echo  
  
- alias: "beacon2 is not active after last presence"  
  trigger:  
    platform: state  
    entity_id: input_boolean.beacon2_trigger  
    to: "off"  
    for: 140  
  action:  
    - service: input_boolean.turn_off  
      entity_id: input_boolean.beacon2_active  
    - service: notify.alexa_media  
      data:  
        message: "Stefano è partito"  
        data:  
          type: announce  
          method: all  
        target:  
          - show  
          - Echo
```

panel

```
type: entities
```

```

entities:
  - entity: input_boolean.beacon2_learn
  - entity: input_text.beacon2
  - entity: input_boolean.beacon2_trigger
  - entity: input_boolean.beacon2_active
title: Tracker cancello

```

esphome

```

esp32_ble_tracker:
  on_ble_advertise:
    - then:
      - homeassistant.service:
          service: script.set_ibeacon
          data:
            ibeacon: !lambda |-
              for (auto data : x.get_manufacturer_datas()) {
                auto message = hexencode(data.data);
                ESP_LOGD("ble_adv", "manufacturer_data: %s [%d]",
message.c_str(), message.size());
                if (message.size() >= 73) {
                  /* ibeacon = e2c56db5-dffb-48d2-b060-d0f5a71096e0 */
                  auto ibeacon = message.substr(6, 2) + message.substr(9, 2)
+ message.substr(12, 2) + message.substr(15, 2) +
                    '-' + message.substr(18, 2) + message.substr(21, 2) +
                    '-' + message.substr(24, 2) + message.substr(27, 2) +
                    '-' + message.substr(30, 2) + message.substr(33, 2) +
                    '-' + message.substr(36, 2) + message.substr(39, 2) +
message.substr(42, 2) + message.substr(45, 2) + message.substr(48, 1);
                  return ibeacon.c_str();
                }
              }
            return "";

```

## BLE bluetooth tracker (version 2)

```

text_sensor:
  - platform: template
    name: "BLE ibeacon"
    id: template_text

esp32_ble_tracker:
  on_ble_advertise:
    - then:
      - lambda: |-
          for (auto data : x.get_manufacturer_datas()) {
            auto message = hexencode(data.data);
            ESP_LOGD("ble_adv", "manufacturer_data: %s [%d]",

```

```
message.c_str(), message.size());
    if (message.size() >= 73) {
        /* ibeacon = e2c56db5-dffb-48d2-b060-d0f5a71096e0 */
        auto ibeacon = message.substr(6, 2) + message.substr(9, 2) +
message.substr(12, 2) + message.substr(15, 2) +
        '-' + message.substr(18, 2) + message.substr(21, 2) +
        '-' + message.substr(24, 2) + message.substr(27, 2) +
        '-' + message.substr(30, 2) + message.substr(33, 2) +
        '-' + message.substr(36, 2) + message.substr(39, 2) +
message.substr(42, 2) + message.substr(45, 2) + message.substr(48, 1);
        id(template_text).publish_state(ibeacon.c_str());
    }
}
```

## BLE bluetooth tracker (deprecated)

parameters to change:

- uuid: "02.15.E2.C5.6D.B5.DF.FB.48.D2.B0.60.D0.F5.A7.10.96.E0.00.01.00.02.C8 (23)"
- name: "scipio cell"

binary\_sensor:

- platform: template
- device\_class: presence
- name: "scipio cell"
- id: beacon1

script:

- id: ble\_off\_script
- mode: restart
- then:
  - binary\_sensor.template.publish:
    - id: beacon1
    - state: true
  - delay: 60s
  - binary\_sensor.template.publish:
    - id: beacon1
    - state: false

esp32\_ble\_tracker:

on\_ble\_advertise:

- then:

- lambda: |-

```
for (auto data : x.get_manufacturer_datas()) {
    if (strcmp(hexencode(data.data).c_str(),
```

```
"02.15.E2.C5.6D.B5.DF.FB.48.D2.B0.60.D0.F5.A7.10.96.E0.00.01.00.02.C8 (23)")
== 0) {
```



```
    ESP_LOGD("ble_adv", "beacon1 found");
    id(ble_off_script).execute();
  }
  else
  {
    ESP_LOGD("ble_adv", "    - %s", hexencode(data.data).c_str());
  }
}
```

From:

<https://wiki.csgalileo.org/> - **Galileo Labs**

Permanent link:

<https://wiki.csgalileo.org/projects/internetofthings/esphome?rev=1625488295>

Last update: **2021/07/05 14:31**

