

# ESPHOME

## ESP32 cam

```
#!/bin/sh

TOKEN=...

PAYLOAD="{\"directive\": {\"header\": {\"namespace\": \"Alexa.Discovery\",
\"name\": \"Discover\", \"payloadVersion\": \"3\", \"messageId\":
\"8db404f7-f5a1-495e-9a30-3a8af3bf94e0\"}, \"payload\": {\"scope\":
{\"type\": \"BearerToken\", \"token\": \"...\"}}}}\"

curl -q -X POST \
-d \"$PAYLOAD\" \
-H \"Authorization: Bearer $TOKEN\" \
-H \"Content-Type: application/json\" \
http://localhost:8123/api/alexasmart_home | jq
'.event.payload.endpoints[] | select(.displayCategories[0]==\"CAMERA\")'
```

in esp32 cam this section is missing in “capabilities”

```
{
  "type": "AlexaInterface",
  "interface": "Alexa.CameraStreamController",
  "version": "3",
  "cameraStreamConfigurations": [
    {
      "protocols": [
        "HLS"
      ],
      "resolutions": [
        {
          "width": 1280,
          "height": 720
        }
      ],
      "authorizationTypes": [
        "NONE"
      ],
      "videoCodecs": [
        "H264"
      ],
      "audioCodecs": [
        "AAC"
      ]
    }
  ]
}
```

```
]
},
```

esp32 entry (missing some values)

```
{
  "displayCategories": [
    "CAMERA"
  ],
  "cookie": {},
  "endpointId": "camera#citofono",
  "friendlyName": "citofono",
  "description": "camera.citofono via Home Assistant",
  "manufacturerName": "Home Assistant",
  "additionalAttributes": {
    "manufacturer": "Home Assistant",
    "model": "camera",
    "softwareVersion": "2021.6.6",
    "customIdentifier": "-camera.citofono"
  },
  "capabilities": [
    {
      "type": "AlexaInterface",
      "interface": "Alexa.EndpointHealth",
      "version": "3",
      "properties": {
        "supported": [
          {
            "name": "connectivity"
          }
        ]
      },
      "proactivelyReported": true,
      "retrievable": true
    }
  ],
  {
    "type": "AlexaInterface",
    "interface": "Alexa",
    "version": "3"
  }
]
```

valid stream camera working in alexa

```
{
  "displayCategories": [
    "CAMERA"
  ],
  "cookie": {},
```

```
"endpointId": "camera#cancello",
"friendlyName": "camera cancello",
"description": "camera.cancello via Home Assistant",
"manufacturerName": "Home Assistant",
"additionalAttributes": {
  "manufacturer": "Home Assistant",
  "model": "camera",
  "softwareVersion": "2021.6.6",
  "customIdentifier": "-camera.cancello"
},
"capabilities": [
  {
    "type": "AlexaInterface",
    "interface": "Alexa.CameraStreamController",
    "version": "3",
    "cameraStreamConfigurations": [
      {
        "protocols": [
          "HLS"
        ],
        "resolutions": [
          {
            "width": 1280,
            "height": 720
          }
        ],
        "authorizationTypes": [
          "NONE"
        ],
        "videoCodecs": [
          "H264"
        ],
        "audioCodecs": [
          "AAC"
        ]
      }
    ]
  },
  {
    "type": "AlexaInterface",
    "interface": "Alexa.EndpointHealth",
    "version": "3",
    "properties": {
      "supported": [
        {
          "name": "connectivity"
        }
      ],
      "proactivelyReported": true,
      "retrievable": true
    }
  }
]
```

```
    },  
    {  
      "type": "AlexaInterface",  
      "interface": "Alexa",  
      "version": "3"  
    }  
  ]  
}
```

## BLE tracker smartband

### esphome

enable esp32\_ble\_tracker and a binary sensor on ble\_presence

```
esp32_ble_tracker:  
  
binary_sensor:  
  - platform: ble_presence  
    mac_address: E8:36:FD:20:E3:54  
    id: miband_presence_scipio  
    name: "MiBand presence scipio"
```

### hass

automation directly on sensor created by esphome

```
- alias: cancello  
  trigger:  
    - entity_id: binary_sensor.miband_presence_scipio  
      platform: state  
      to: 'on'  
      for:  
        seconds: 2  
    - entity_id: binary_sensor.miband_presence_scipio  
      platform: state  
      to: 'off'  
      for:  
        seconds: 2  
  action:  
    - service: notify.alexmedia  
      data_template:  
        message: >  
          {% if is_state('binary_sensor.miband_presence_scipio', 'on') %}  
            'Stefano è arrivato'  
          {% else %}
```

```

        'Stefano è partito'
    {% endif %}
data:
  type: announce
  method: all
target:
  - show
  - Echo

```

example of added binary sensor defined on ble sensor

```

binary_sensor:
  - platform: template
    sensors:
      miband_scipio_sticky:
        value_template: >-
          {{is_state('binary_sensor.miband_presence_scipio', 'on')}}
        delay_off: 60

```

## BLE bluetooth tracker (version 1)

hass input\_boolean:

```

beacon2_learn:
  name: learn beacon2
  initial: off
  icon: mdi:mdi-tag-plus

beacon2_active:
  name: beacon2 is recently seen
  icon: mdi:mdi-account-check

beacon2_trigger:
  name: beacon2 is now detected
  initial: off
  icon: mdi:mdi-account-check

```

hass input\_text:

```

beacon1:
  name: BLE beacon1

beacon2:
  name: BLE beacon2

```

hass scripts:

```

set_ibeacon:
  sequence:

```

- condition: template  
value\_template: "{{ ibeacon != ' ' }}"
- service: script.set\_beacon1  
data\_template:  
  ibeacon: "{{ ibeacon }}"
- service: script.set\_beacon2  
data\_template:  
  ibeacon: "{{ ibeacon }}"

set\_beacon2:

- sequence:
  - service: script.beacon2\_active  
data\_template:  
  ibeacon: "{{ ibeacon }}"
  - condition: state  
entity\_id: input\_boolean.beacon2\_learn  
state: "on"
  - service: input\_text.set\_value  
data\_template:  
  entity\_id: input\_text.beacon2  
  value: "{{ ibeacon }}"
  - service: input\_boolean.turn\_off  
entity\_id: input\_boolean.beacon2\_learn

beacon2\_active:

- sequence:
  - condition: template  
value\_template: "{{ ibeacon == states('input\_text.beacon2') }}"
  - service: input\_boolean.turn\_on  
entity\_id: input\_boolean.beacon2\_trigger
  - delay: 1
  - service: input\_boolean.turn\_off  
entity\_id: input\_boolean.beacon2\_trigger

hass automations:

- alias: "beacon2 is active"  
trigger:  
  platform: state  
  entity\_id: input\_sensor.beacon2\_trigger  
  to: "on"  
condition:  
  condition: state  
  entity\_id: input\_boolean.beacon2\_active  
  state: "off"  
action:
  - service: input\_boolean.turn\_on  
  entity\_id: input\_boolean.beacon2\_active
  - service: notify.alex\_media

```

data:
  message: "Stefano è arrivato"
  data:
    type: announce
    method: all
  target:
    - show
    - Echo

- alias: "beacon2 is not active after last presence"
  trigger:
    platform: state
    entity_id: input_boolean.beacon2_trigger
    to: "off"
    for: 140
  action:
    - service: input_boolean.turn_off
      entity_id: input_boolean.beacon2_active
    - service: notify.alexa_media
      data:
        message: "Stefano è partito"
        data:
          type: announce
          method: all
        target:
          - show
          - Echo

```

panel

```

type: entities
entities:
  - entity: input_boolean.beacon2_learn
  - entity: input_text.beacon2
  - entity: input_boolean.beacon2_trigger
  - entity: input_boolean.beacon2_active
title: Tracker cancello

```

esphome

```

esp32_ble_tracker:
  on_ble_advertise:
    - then:
      - homeassistant.service:
          service: script.set_ibeacon
          data:
            ibeacon: !lambda |-
              for (auto data : x.get_manufacturer_datas()) {
                auto message = hexencode(data.data);
                ESP_LOGD("ble_adv", "manufacturer_data: %s [%d]",
message.c_str(), message.size());

```

```
        if (message.size() >= 73) {
            /* ibeacon = e2c56db5-dffb-48d2-b060-d0f5a71096e0 */
            auto ibeacon = message.substr(6, 2) + message.substr(9, 2)
+ message.substr(12, 2) + message.substr(15, 2) +
                '-' + message.substr(18, 2) + message.substr(21, 2) +
                '-' + message.substr(24, 2) + message.substr(27, 2) +
                '-' + message.substr(30, 2) + message.substr(33, 2) +
                '-' + message.substr(36, 2) + message.substr(39, 2) +
message.substr(42, 2) + message.substr(45, 2) + message.substr(48, 1);
            return ibeacon.c_str();
        }
    }
    return "";
```

## BLE bluetooth tracker (version 2)

```
text_sensor:
- platform: template
  name: "BLE ibeacon"
  id: template_text

esp32_ble_tracker:
  on_ble_advertise:
    - then:
      - lambda: |-
          for (auto data : x.get_manufacturer_datas()) {
              auto message = hexencode(data.data);
              ESP_LOGD("ble_adv", "manufacturer_data: %s [%d]",
message.c_str(), message.size());
              if (message.size() >= 73) {
                  /* ibeacon = e2c56db5-dffb-48d2-b060-d0f5a71096e0 */
                  auto ibeacon = message.substr(6, 2) + message.substr(9, 2) +
message.substr(12, 2) + message.substr(15, 2) +
                      '-' + message.substr(18, 2) + message.substr(21, 2) +
                      '-' + message.substr(24, 2) + message.substr(27, 2) +
                      '-' + message.substr(30, 2) + message.substr(33, 2) +
                      '-' + message.substr(36, 2) + message.substr(39, 2) +
message.substr(42, 2) + message.substr(45, 2) + message.substr(48, 1);
                      id(template_text).publish_state(ibeacon.c_str());
              }
          }
```

## BLE bluetooth tracker (deprecated)

parameters to change:

- uuid: "02.15.E2.C5.6D.B5.DF.FB.48.D2.B0.60.D0.F5.A7.10.96.E0.00.01.00.02.C8 (23)"
- name: "scipio cell"

binary\_sensor:

- platform: template
- device\_class: presence
- name: "scipio cell"
- id: beacon1

script:

- id: ble\_off\_script
- mode: restart
- then:
  - binary\_sensor.template.publish:
    - id: beacon1
    - state: true
  - delay: 60s
  - binary\_sensor.template.publish:
    - id: beacon1
    - state: false

esp32\_ble\_tracker:

```
on_ble_advertise:
  - then:
    - lambda: |-
        for (auto data : x.get_manufacturer_datas()) {
            if (strcmp(hexencode(data.data).c_str(),
"02.15.E2.C5.6D.B5.DF.FB.48.D2.B0.60.D0.F5.A7.10.96.E0.00.01.00.02.C8 (23)")
== 0) {
                ESP_LOGD("ble_adv", "beacon1 found");
                id(ble_off_script).execute();
            }
            else
            {
                ESP_LOGD("ble_adv", "    - %s", hexencode(data.data).c_str());
            }
        }
    }
```

From:

<https://wiki.csgalileo.org/> - Galileo Labs

Permanent link:

<https://wiki.csgalileo.org/projects/internetofthings/esphome?rev=1625488498>

Last update: 2021/07/05 14:34

