

GNSS

- [wonderful introduction on GNSS](#)
- [stations](#) that broadcast real time RTCM (protocol) Radio Technical Commission for Maritime
- [ubxtool examples](#)
- NEO-M9N
- ZED-F9P

2022

Use gpsd as [ntrip client](#) on ublox device

pygnssutils

Configure ublox as [base station](#) and run an ntrip server with [PyGPSClient](#)

2020

ntrip caster

- <https://gitlab.com/ihfazhillah/simple-ntrip-caster/-/tree/master>
- <https://gitlab.com/hydrasystem/ntripcaster.git>

sourcetable.dat

```
CAS;rtcm-
ntrip.org;2101;NtripInfoCaster;BKG;0;DEU;50.12;8.69;http://www.rtcn-ntrip.org/home
STR;castagne;Verona;RTCM3;none;1;none;TEST;ITA;45.4935250;11.1068889;421;0;receiver5;none;B;N;3600;none
```

test caster, must return source table

```
curl http://192.168.2.50:2101
```

ntrip base station

configure ublox in NMEA

```
systemctl stop gpsd
systemctl stop gpsd.socket

DEVICE=/dev/gps0
ubxtool -f $DEVICE -p RESET
```

```
ubxtool -f $DEVICE -e NMEA
ubxtool -f $DEVICE -d BINARY
ubxtool -f $DEVICE -p SAVE
```

ntrip source

```
str2str -in 'serial://ttyACM0:115200#stq' -out
'ntrips://mev@localhost:2101/castagne#rtcm2' -p 45.4935250 011.1068889 421
-msg "1004,1006,1019,1033,1012,1030"
```

GPS

```
gpsd -N -n -D3 /dev/gps0 # no -b option
```

with DGPS

```
gpsd -N -n -D3 /dev/gps0 ntrip://NTRIP.itsware.net:2101/AB50_RTCM3
psd -N -n -D1 /dev/gps0 ntrip://rtk2go.com:2101/MEV0
```

```
ubxtool -p MON-VER
```

UBX-MON-VER:

```
swVersion EXT CORE 1.00 (61b2dd)
hwVersion 00190000
extension ROM BASE 0x118B2060
extension FWVER=HPG 1.12
extension PROTVR=27.11
extension MOD=ZED-F9P
extension GPS;GL0;GAL;BDS
extension QZSS
```

```
export UBXOPTS="-P 27.11 -v 2"
ubxtool -p RESET
ubxtool -e BINARY
ubxtool -e NMEA
```

get current dynamic mode

```
ubxtool -p CFG-NAV5
```

```
...
dynModel (Portable)
...
```

or

```
ubxtool -p CFG-NAV5 | grep dynModel
```

switch model to automotive

```
ubxtool -p MODEL,4
ubxtool -p SAVE
```

udev

[/etc/udev/rules.d/91-ubox.rules](#)

```
#SUBSYSTEMS=="usb", DRIVERS=="usb", ACTION=="add",
ATTRS{idVendor}=="1546", ATTRS{idProduct}=="01a9", SYMLINK+="gps0",
MODE="0666"
ATTRS{idVendor}=="1546", ATTRS{idProduct}=="01a9", SYMLINK+="gps%n",
TAG+="systemd", ENV{SYSTEMD_WANTS}="gpsdctl@%k.service"
```

[/etc/default/gpsd](#)

```
START_DAEMON="false"
# binary mode for ublox
GPSD_OPTIONS="-b"
DEVICES=""
USBAUTO="true"
```

test

- <https://gpsd.gitlab.io/gpsd/ppp-howto.html>

```
gpsd -b -N /dev/ttyACM0
```

```
gpspipe -r | nc -l 29999
```

```
yay -S qt5-location
```

qml

```
import QtQuick 2.1
import QtQuick.Window 2.0
import QtPositioning 5.5
import QtLocation 5.6
```

```
Window {
    id:page
    width: 1024
    height: 1024
    visible: true
```

```
Map {
```

```
id:myMap
anchors.fill: parent
plugin: mapPlugin
zoomLevel: 23

property MapCircle circle

function update(pos) {
    removeMapItem(circle);

    circle = Qt.createQmlObject('import QtLocation 5.3; MapCircle {}',
page);
    circle.radius = 2;
    circle.color = "transparent";
    circle.border.color = "red"
    circle.border.width = 3;
    myMap.addMapItem(circle);

    circle.center = pos.coordinate;
    myMap.center = pos.coordinate;

    //console.log("Coordinates: ", pos.coordinate.latitude,
pos.coordinate.longitude);
}
}

Plugin {
    id: mapPlugin
    name: "osm"
}

PositionSource {
    id: gpsPos
    updateInterval: 500
    active: true
    nmeaSource: "socket://localhost:29999"

    onPositionChanged: {
        myMap.update(position);
    }
}
}
```

From:
<https://wiki.csgalileo.org/> - Galileo Labs

Permanent link:
<https://wiki.csgalileo.org/tips/gnss>

Last update: 2022/08/25 23:03



